

## ANTENNA AD1602

HORWIN AD 1602 is a two-dipole element array wide band VHF antenna for professional radio systems.


Dipole incorporates "balun" matching circuit optimized for wide bandwidth and accurate matching. More gain is achieved by coupling single folded dipoles into arrays. Dipoles in array are coupled by precision phasing cable harness keeping low SWR and minimum insertion losses.

The horizontal radiation pattern is adjusted by changing the distance between dipole elements and supporting mast. All antenna parts are made of aluminium and covered with polymer powdered coating which resists water and ice buildup, and provides exceptional protection from corrosive gases, UV radiation, salt spray, acid rain and windblown abrasives. All components of dipole elements are DCgrounded for better lightning and antistatic protection.




		AD1602
Frequency range, MHz		136 – 176
Bandwidth @ SWR < 1,5, MHz		40
Elements		2
Gain, dBd (1/4 λ dipole to mast spacing)		3
Gain, dBd (3/8 λ dipole to mast spacing)		5,6
Power rating, W		200
Overall dimensions, mm	H	2200
5/8λ spacing	D	1100
Weight (aprox.), kg		5,9
Impedance, Ohm		50
Termination		N- female
Vertical beamwidth (3/8 spacing)		38°
Max. exposed area, m <sup>2</sup>		0,14
Lateral thrust at 45 m/s, H		165
Lightning protection		CD Ground
Rated wind velocity, m/s		45
Rated wind velocity with 0.5" icing, m/s		28

E-plane 1/4 λ dipole to mast spacing



E-plane 3/8 λ dipole to mast spacing



H-plane (Horwin AD 1602)

