


ANTENNA AD1601

HORWIN AD 1601 is a one-dipole element array wide band VHF antenna for professional radio systems. Dipole incorporates "balun" matching circuit optimized for wide bandwidth and accurate matching. The horizontal radiation pattern is adjusted by changing the distance between dipole element and supporting mast. All antenna parts are made of aluminium and covered with polymer powdered coating which resists water and ice buildup, and provides exceptional protection from corrosive gases, UV radiation, salt spray, acid rain and windblown abrasives. All components of dipole element are DCgrounded for better lightning and antistatic protection.




		AD1601
Frequency range, MHz		136 – 176
Bandwidth @ SWR < 1,5, MHz		40
Elements		1
Gain, dBd (1/4 λ dipole to mast spacing)		0
Gain, dBd (3/8 λ dipole to mast spacing)		3
Power rating, W		200
Overall dimensions, mm	H	900
	D	1100
Weight (aprox.), kg		2,8
Impedance, Ohm		50
Termination		N- female
Vertical beamwidth (3/8 spacing)		70°
Max. exposed area, m ²		0,07
Lateral thrust at 45 m/s, H		80
Lightning protection		CD Ground
Rated wind velocity, m/s		45
Rated wind velocity with 0.5" icing, m/s		28

E-plane ¼ λ dipole to mast spacing



E-plane 3/8 λ dipole to mast spacing



H-plane (Horwin AD 1601)

